

Спецификация продукта

Имя продукта: цифровой термометр жт002нм

Блок питания: 1,5 DC, батарея кнопки 1лр41.

Потребляемая мощность: 0,1 МВт

Срок службы аккумулятора: около 1100 чтения (если используется в течение 10 минут в день)

Чувствительный блок: термистор

Метод измерения: фактическое измерение

Дисплей температуры: 3-значный, + °с (°f) дисплей в 0,1 градуса увеличивает

Точность измерения: ± 0.1 °с (32 °с -43 °с)

$\pm 0,18$ °f (89.60 °f-109.40 °f)

Время измерения: 2М

Диапазон измерения: 32 °с до 43 °с (89.6 °f до 109.40 °f)

Использование окружающей среды: Окружающая температура: + 10 °с до + 40 °с (50 °f до 104 °f)

Среда хранения:-20 °с до + 60 °с (-4 °f до 140 °f)

Температура и влажность: относительная влажность 30-95% RH

Вес: приблизительно. 15g (батарея включена)

Габариты: 20мм (W) * 130мм (l) * (d)

Вспомогательное оборудование: батарея испытания (щелочная-магний батарея кнопки LR4), случай хранения, руководство потребителя.

Упаковка: 80pcs/кор

Размер: 331мм * 305мм * 260мм

show details

01 battery cover

This product USES the button battery, push the battery cover and replace the battery



02 Internal Battery

Open the battery cover to see the internal details determine the quality



03 Elliptic switch

A button switch, convenient and concise




04 LED display screen

The LED screen shows the digital value is more intuitive



05 Heat detector

Using soft head probe, safe and convenient



Методы измерения продукта:

